



Ruggedized and featuring excellent temperature flexibility while delivering top performance, Transcend's CF220I Industrial Temp CF cards are specifically designed for industrial use and mission-critical applications.

Hardware Features

- · Compliant with RoHS 2.0 standards
- Compliant with CompactFlash specification 6.0
- Durability: 10,000 insertion/removal cycles
- Promised operational reliability in a wide temperature range (from -40°C to 85°C)
- Power Shield (PS) to ensure data transfer integrity and minimize data corruption in the drive during an abnormal power outage

Firmware Features

- Operation modes supported: PC Card Memory mode, PC Card IO mode, and True IDE mode
- Supports S.M.A.R.T. function to conduct health monitoring, analysis, and reporting for storage devices
- Security Command
- Wear-Leveling
- · Static Data Refresh

Ordering Information


512MB	TS512MCF220I	
1GB	TS1GCF220I	
2GB	TS2GCF220I	
4GB	TS4GCF220I	



Specifications

Appearance	Dimensions	42.8 mm x 36.4 mm x 3.3 mm (1.69" x 1.43" x 0.13")
	Pin Count	50 pin
Storogo	Form Factor	Compact flash card
	Flash Type	SLC NAND flash
Storage Operating Environment	Capacity	512 MB /1 GB /2 GB /4 GB
	Operating Voltage	3.3V±5% 5V±10%
	Operating Temperature	Wide Temp. -40°C (-40°F) ~ 85°C (185°F)
	Storage Temperature	-55°C (-67°F) ~ 100°C (212°F)
	Humidity	0% ~ 95%
	Shock	15 G, 11 ms, 3 axis
	Vibration (Operating)	20 G (peak-to-peak), 20 Hz ~ 2,000 Hz (frequency)
Power	Power Consumption (Max.)	0.52 watt(s)
Performance	Read Speed (Max.)	Up to 46 MB/s
	Write Speed (Max.)	Up to 39 MB/s
	Mean Time Between Failures (MTBF)	3,000,000 hour(s)
Warranty	Warranty	Three-year Limited Warranty

Mechanical Dimensions



Product specifications are subject to change without notice. Pictures shown may differ from actual products. Total accessible capacity varies depending on operating environment. Due to the complexity and variety of industrial applications, Transcend cannot guarantee 100% compatibility with all platforms and under all scenarios. For special applications and environments, it is strongly suggested that you contact Transcend beforehand for clarification.